

Morserino-32 Firmware UPDATE (N3GE 1/24/2021)

Tip: You can update to any version, "jump" versions, OR go back to an older version.

ON COMPUTER: Get the binary file from the Morserino-32 repository on GitHub

(<https://github.com/oe1wkl/Morserino-32> -

Look for directory under "Software" called "Binaries".

Get the latest version & download it to your computer. Looks like:

morse_3_vx.y.ino.wifi_lora_32.bin (x.y = version number).

FOR 4.0:

https://github.com/oe1wkl/Morserino-32/blob/master/Software/binary/m32_v4.0.ino.wifi_lora_32_V2.bin

FOR 4.0.1: bug fix release V4.0.1 on 1/23/2021

https://github.com/oe1wkl/Morserino-32/blob/master/Software/binary/m32_v4.0.1.ino.wifi_lora_32_V2.bin

ON MORSERINO: WiFi Functions; Update Firmw
Single Click **BLACK** button

ON COMPUTER: Similar to file upload, on your computer browser, type:

<http://m32.local>

At M32 Firmware Update Login Page: USERNAME **m32**

PASSWORD **update**

Login

On m32.local web page: Choose file; SELECT from DOWNLOADS M32 . . .bin

Begin

MORSERINO: WILL RESTART & SHOW NEW VERSION